

M485-AD16U20-I

20 x analog or 10 x differential inputs, 0 - 20ma, +/- 10 volts, 16bit solution, sample speed 10Hz, RS485.
10 - 30vdc.

FEATURES

- 20 channel analog input module for RS485 Bus
- 16bit resolution
- 20 Single Ended inputs (common frame) - Only for Volt
- 10 differential entrances for volts about power
- 10 measurements per second (Total)
- Jumper Setting in the module
- Supply voltage: 10 - 30vdc / 1.3 watts
- Dim: 123 x 72 x 35 mm
- DIN bracket





M485-AD16U20-I

SPECIFICATIONS

Forsyning	:	10 - 30 VDC, 2 W via klemrække
Indgang	:	10 differentielle eller 20 "single-ended" indgange
Indgangsimpedans	:	2 MΩ ved differentiell og 1 MΩ ved single ended 125 Ω ved strømmåling
Isolation	:	3000 VDC
Maks. hastighed	:	60 målinger pr. sek. ved 12 bit og 10 målinger pr. sek. ved 16 bit (totalt på alle 10/20 indgange)
Måleområde	:	±150 mV, ±500 mV, ±1 V, ±5 V, ±10 V samt ±20 mA, 0-20 mA og 4-20 mA
Opløsning	:	12/16 bit. ±0,1 % præcision ved 16 bit og ±0,5 % præcision ved 12 bit
Stabilitet	:	Nulpunktsdrift: ±20 µV/°C Drift af følsomhed: ±25 ppm/°C

