

M485-COUNT-I

2 channel frequency counter module with 2 inputs,
max. 100kHz. 32 bits count. 2 x digital output.

FEATURES

- RS485 Frequency counter with 2 digital outputs
- 2 x counter entrance Max. 100kHz
- input is Wet / Sink - Max + 30volt
- 32 bit counter - count up for frequency and pulses
- 2 X Digital Output - Open Collector (OC)
- Max. OC voltage: 30VDC / 30MA
- Supply voltage: 10 - 30VDC
- Dim: 123 x 72 x 35 mm
- Operating temperature: -25 - + 75 ° C





SPECIFICATIONS

Forsyning	:	10 - 30 VDC, 2 W via klemrække
Features	:	Programmerbart digitalt støjfilter: 2 μ - 65 ms
Indgang	:	2 stk. 32 bit tællere, valgfrit isoleret eller ikke-isoleret
Isolation	:	Isoleret indgang (2500 VRMS): "0": 0 - 1 V , "1": 3,5 - 30 V Ikke-isoleret indgang med programmerbar tærskelværdi
Maks. hastighed	:	Frekvens: 1 Hz - 100 kHz, Gate-tid: 0,1 eller 1 sek. Impulsbredde: Min. 10 μ s
Udgange	:	2 stk. "Open collector" 30 V/30 mA

