

22" 16:9 Industrial monitor, With resistive touch, VGA, HDMI, External dimming to adjust the brightness. Option: 1000Nits

FEATURES

22" (16:9)
Resolution: 1920x1080
Inputs: VGA, HDMI
Resistive Touch (Option: Projective Glass, SAW)
USB. (option: RS232)
OSD
Operating temperature: 0 ~ 50°C
Supply voltage: 12Vdc
Option: 1000 nits





SPECIFICATIONS

Operating Temp.	:	0~50C
Andet	:	External DIMM knob for adjusting from 0 to 100%
Antal farver	:	16.7M (8bit/color)
Betragningsvinkel	:	-89~89(H) ; -89~89(V)
Forsyning	:	12Vdc (2.5) with external AC-DC adapter (100~240Vac)
Indgang	:	1xVGA, 1xHDMI
Kontrast	:	3000:1 (typical)
Lyd	:	OPTION! Audio line in (3.5mm) + 2xSpeaker
Lysstyrke	:	250 cd/m(typical)
Skærm	:	476,64 (H) x 269.11 (V)
Skærm	:	22" 16:9
Strømforbrug	:	Typical 40W normal operation





Svensk Binär Teknik

MON22-PW-T-DIMM

SPECIFICATIONS



Binär Teknik AB
Lugna Gaten 39 Malmö, 211 59 Sweden



042 14 10 85



salg@danbit.dk

For business customers only (B2B). Prices exclude VAT. We reserve the right to correct errors and make changes.