

PCMCIA card reads with USB Interface reads from
20MB to 20GB Memory Ata Card not reading all
cards!

FEATURES

USB 2.0, USB 1.1

Power from USB or AC / DC power adapter
read and write to PCMCIA hard disk, ATA Flash.

DOES NOT READ SPECIAL CARDS!

read and write to CF-I, CF-II Smart Memory, Memory
Stick, Micro Drive, Multimedia Card, Secure Digital
Card and XD

Card use of additional Flash adapter.

Complete Plug and Play

USB Bootable from PCMCIA hard drive (depending
on system BIOS support)

Serial ATA bootable from PCMCIA hard drive

Up to 480 Mbit/sec (60 MB/sec) data transfer* for
USB 2.0, 10 times the speed of USB 1.1

Up to 1500 Mbit / second (150 MB / sec) data
transfer to eSATA

USB version works under Windows 98SE, Me, 2000,
XP, 7, 2003, Windows 10

Note! Certain cards are not supported Memory card
and Verifone card. Buy the cards together with the
reader to be sure!

Will not be returned because card cannot be read.

Send any short, then we test whether the reader
can read them.





Svensk Binär Teknik

PCM-USB+A

SPECIFICATIONS

OS SUPPORT

:



Binär Teknik AB
Lugna Gaten 39 Malmö, 211 59 Sweden



042 14 10 85



salg@danbit.dk

For business customers only (B2B). Prices exclude VAT. We reserve the right to correct errors and make changes.