



Svensk Binär Teknik

USB-AD5S16

5 x analog inputs and 2 x analog output, 2 x digital input and 2 x digital output via USB

FEATURES

- 5 kanals analog input
- 2 kanals analog output
- 2 kanals digital input
- 2 kanals digital output



Binär Teknik AB
Lugna Gaten 39 Malmö, 211 59 Sweden



042 14 10 85



salg@danbit.dk

For business customers only (B2B). Prices exclude VAT. We reserve the right to correct errors and make changes.



SPECIFICATIONS

Indgang	:	2 stk digital kontakt indgange
Måleområde	:	Spænding: ± 1 V, ± 2.5 V, ± 5 V, ± 10 V. Strøm: ± 20 mA, 0 - +20 mA, +4 - +20 mA
Software	:	USB driver til Windows 2000, XP, Win7 og Win8. Programmeringseksempler i VB, C++, C#.NET, VB.NET medfølger
Udgange	:	2 stk. 0 - 5V, 0-10 V, ± 5 V, ± 10 V samt +0 - 20 mA, 4 - 20 mA Opløsning 12 bit $\pm 0,1$ % af FSR
Udgange	:	2 stk open collector maks 700mA/ 50 Volt
Dimensioner	:	33 mm $\times$ 107 mm $\times$ 78 mm (B x H x D)

