

BOOST-HDMI150-U+IR

HDMI KVM extender, 150 meters over Cat 6a / 7 RJ45 cable, or over TCP/IP, USB HID

FEATURES

Transmits HDMI video and audio and USB up to 150 meters over network cable

Transfers HDMI video and audio and USB over local network

USB is for keyboard and mouse only Set with transmitter and receiver 1920 x 1080 @60Hz

A transmitter to multiple receivers over non-managed switch.


Supports keyboard and mouse ONLY Supports TCP/IP and local EDID

HDMI 1.3 / HDCP 1.2

Transmitter: 1 x HDMI, 1 x USB-B, 1 x RJ45 Ethernet Receiver: 1 x HDMI, 2 x USB-A, 1 x RJ45 Ethernet

built-in auto-adjustment system
Built-in ESD protection system
Power supply: DC 5V/1A (supplied)
Dimensions: 92 x 70 x 25 mm





BOOST-HDMI150-U+IR

-	~ —	\sim 1 I	- 1 -	` ^ _	-	NS
	ᄼ		- 16	Λ		\sim

PC: Type B USB interface; connect to PC; K/M: connect USB keyboard

and mouse;

Operating Temp. : $-5 \sim +70$

Data : 6.75Gbps

Indgang : HDMI-A

Netværk : RJ45 CAT 6 - 150 meter- Cat7 - 180 meter

Opløsning : 1920X1080@60Hz

Strømforbrug : MAX 3W

Strømforsyning : DC 5V/1A

Dimensioner : 92*70*25mm